



DRR-103

Digital Radio Receiver

The Digitalview DRR-103 is a class leading Digital Radio Receiver supporting the latest advances in digital and analog radio reception including Pause Live Radio for digital reception. The DRR-103 allows the listener to tune to any of their available local DAB+ and FM/RDS broadcasts, anywhere in Australia.

Connecting the DRR-103 to any existing hi-fi system is extremely easy. The user has a choice of using analog or digital audio formats. All information related to reception and the operation of the DRR-103 is provided on a large high contrast LCD display. Where simple system integration is required for home automation, the DRR-103 provides an IR control interface.

The DRR-103 styling is designed to visually complement any existing hi-fi or music listening installation, based on individual system components. Overall construction is of the highest quality, with all mechanical and electronic parts selected to provide long term reliability.



DRR-103 Main Features

- DAB+ and FM/RDS Reception
- Pause Live Radio with Fast Forward And Rewind (240 minutes duration over a twelve hour period)
- 20 User Assignable Presets each for DAB+ and FM
- Digital Audio Output - S/PDIF Optical and Coaxial
- Home Automation Control Interface - IR with 3.5mm RTS socket
- Hi-Fi Component Footprint (430mm width)
- Complies with MEPS for low power (0.6W) in Standby mode



Front Panel



Rear Panel

DRR-103 Specification

Type:	Digital / Analog Radio Receiver (DAB+/FM)
Frequency Range	FM: 87.50MHz to 108MHz DAB Band 3: 174.928MHz to 239.20MHz L-Band: 1452.960MHz - 1490.624MHz
Supported Audio Formats	AAC+
Frequency Response	FM: Typically 20Hz - 15kHz @ -3db DAB: Typically 20Hz - 20kHz and only limited by broadcast Analog Audio O/P: 20Hz - 20KHz
Sensitivity	FM -108dbm typical DAB and L-Band - 97dbm typical
Signal to Noise	FM 50dbA typical DAB 99dbA typical
THD Distortion (Analog Output)	0.01% typical
Signal to Noise (Analog Output)	97db typical
Antenna Input Impedance - DAB, DAB+, FM	75 ohm - "F" type connector
Digital Audio Output/s	S/PDIF - Optical and Coaxial
Analog Audio Output	L & R Channels (RCA)
Pause Live Radio Duration	240 minutes with Fast Forward and Rewind functionality relative to the current time
Control Interface	Discrete IR (3.5mm ring/tip socket)
Input Voltage / Frequency	180 - 265VAC / 47-60Hz
Power Consumption (max.)	< 1.5W
Power in Standby	< 0.6W
Operating Temperature / Humidity	0 - 50°C / 5% -90% Non-condensing
Dimensions (max.)	430mm(W) x 207mm(D) x 66mm(H)
Warranty	One Year



Where applicable, any Logos and/or Trademarks used in this document are copyright by their respective owners.

Specification is subject to change without prior notice.

© 2008 - 2011 Control Dynamics Pty. Ltd.



Digitalview (Australia)
5 Bookham Street, Morley, Western Australia, 6062, Australia
Telephone: +61-8-9275-9700 Facsimile: +61-8-9275-9717
www.digitalview.com.au

Digitalview is a business unit of Control Dynamics Pty. Ltd.
www.controldynamics.com.au

Distributor

PUB:CDAUS-DRR103-180511